

Connecting the charger AXIbox 11K to the App Evchargo

- 1 Register in the App
 - 1) Download and install the App Evchargo



- 2) Activate Wifi, Bluetooth and location.
- 3) Register with your e-mail and log in.

2 Connecting the Charger to the App

- 1) The charger needs to be installed correctly before connecting to the App. Start the charger (green LED flashing slowly).
- 2) Go to "Charge Points" and then to "Bind the Charge point". Select "EN+".

13:34		13:34 🔐 🕈 🗈	
Self-use	Sharing	< Sel	ect the Brand
		Select the Brand Ac	
((+ -))		Select the Brand of ch	arge point:
Bind the charge point with APP, then charge point by mobile phone.	you can control the	MALMBERG	s FAT•N
		Malmbergs	EATON
		EN⁺	
		EN+	
🕀 Bind the Charge	point		
Charge Points Map	Q Me	_	

3) Select in the following menu "Check for nearby charge points".

Via Bluetooth, the available chergers are shown. Select the selection field with the serial number of your charger. In the menu "Select the Operator" choose "Shenzen en+123" (almost on the bottom of the list).

<u>Note:</u> It is necessary that the charging station is found via Bluetooth. If this is not the case, the charging station must be reset manually in order to reactivate the Bluetooth of the charging station. To do this, contact the support. Manually entering the serial number or scanning the barcode results in an error.



13:34		13:58		.⊪ ? ■	13:59		
<	Add a charge point	<	Nearby charge point	ts	<	Select the Operator	
(1) Select the E	Grand Add a charge point Config	ure the nication	Brand Add a charge operator		Select the Brand	d Add a charge Select the point operator	
	_	Select y	our charge point:		Select the O	perator of the charge point	
			SN1C		iAcces	ss Corp Ltd	
				VERD	ELED		
				en666	3		
					Shenz	hen en+123	
Sca	n the QR code on the charge poin	t			Zucch	etti Centro Sistemi SpA	
Scan the OD code				Sub 1			
ج Scan the QR code					驿普乐	Æ	
					33333	3333333	
	(+) Add manually				co		
Сс	heck for nearby charge points				mode	nnncark	
					Nettse	evice	

4) Connect to your WIFI (enter Wifi name and password, then confirm).

14:09	ul † ∎⊃	13:29	
Configure the network		Self-use	Sharing
3 Select the Brand Add a charge point Select the operator	Configure the network	ି SN10	-
WiFi Name			
WiFi Password			
	ø	0	0
		Available	2
		Max Charging Current	16A ≫
		Charging schedule	
Confirm		Chort	
Skip		Start	
E Logs upload		Charge Points Map	O Me

The following connecting process takes 30 to 60s to complete. Afterwards, the charger is shown as online and can be controlled via App.